

Position of channel selection jumper when using 6chv2.0 controller

# of channel in control program	description of pins on PCB 12xV4.0R	Name of channel of LEDs	LED driver assembly 2xV1.0M, 7xV1.1 and 2xV1.2	LED driver assembly 2xV1.1	LED driver assembly 7xV1.0	# of pin on controller flat cable
1	3-4 on X1	White	6	2	2	5
2	5-6 on X1	Violet	5	3	3	6
3	5-6 on X2	Royal Blue	4	4	4	7
4	1-2 on X1	Blue	3	5	5	8
5	1-2 on X2	Turquoise	2	6	6	9
6	3-4 on X2	Red	1	7	7	10

Position of channel selection jumper when using 6chv3.0 controller

# of channel in control program	description of pins on PCB 12xV4.0R	Name of channel of LEDs	LED driver assembly 2xV1.0M, 7xV1.1 and 2xV1.2	LED driver assembly 2xV1.1	LED driver assembly 7xV1.0	# of pin on controller flat cable
1	3-4 on X1	White	1	7	7	10
2	5-6 on X1	Violet	2	6	6	9
3	5-6 on X2	Royal Blue	3	5	5	8
4	1-2 on X1	Blue	4	4	4	7
5	1-2 on X2	Turquoise	5	3	3	6
6	3-4 on X2	Red	6	2	2	5