

**Position of channel selection jumper when using 6chv2.0 controller**

# of channel in control program	description of pins on PCB 12xV4.0F	Name of channel of LEDs	LED driver assembly 2xV1.0M, 7xV1.1 and 2xV1.2	LED driver assembly 2xV1.1	LED driver assembly 7xV1.0	# of pin on controller flat cable
1	X2 pin6->X1 pin1	Cool White	6	2	2	5
1	X2 pin1->X1 pin6	Cool White	6	2	2	5
2	X2 pin3->X1 pin4	Neutral White	5	3	3	6
3	X2 pin5->X1 pin2	Blue	4	4	4	7
4	X2 pin4->X1 pin3	Turquoise	3	5	5	8
5	X2 pin2->X1 pin5	Red	2	6	6	9

**Position of channel selection jumper when using 6chv3.0 controller**

# of channel in control program	description of pins on PCB 12xV4.0F	Name of channel of LEDs	LED driver assembly 2xV1.0M, 7xV1.1 and 2xV1.2	LED driver assembly 2xV1.1	LED driver assembly 7xV1.0	# of pin on controller flat cable
1	X2 pin6->X1 pin1	Cool White	1	7	7	10
1	X2 pin1->X1 pin6	Cool White	1	7	7	10
2	X2 pin3->X1 pin4	Neutral White	2	6	6	9
3	X2 pin5->X1 pin2	Blue	3	5	5	8
4	X2 pin4->X1 pin3	Turquoise	4	4	4	7
5	X2 pin2->X1 pin5	Red	5	3	3	6